

## Technische Informationen zum Status – Empfangener Fax

2. Anrufernummer	Diese Nummer kann manuell gesetzt werden, um anstatt die Faxnummer des Gerätes beim Empfänger anzeigen zu lassen, die Nummer der Zentrale anzeigen zu lassen.
Weiterleitungsnummer	Direkte Umleitungsnummer, ohne eine Zentrale zu verwenden.
Remote Fax ID	Die ID vom FAX Gerät.
Rx Speed	Übertragungs-Geschwindigkeit in Empfangsrichtung. Anzahl Zeichen pro Sekunde. 1 Zeichen sind 8 Bit.
Tx Speed	Übertragungs-Geschwindigkeit in Senderichtung. Anzahl Zeichen pro Sekunde. 1 Zeichen sind 8 Bit.
Seitenauflösung	Auflösung von Bild und Text in dpi
MR Aktiv	Modified READ, auch als „Fax Group 3“ oder eindimensionale Kodierung bezeichnet. Die Komprimierungsraten sind abhängig von den Bilddaten, im Allgemeinen liefert MMR jedoch die beste Komprimierung gefolgt von MR.
MMR Aktiv	Modified Modified READ auch als „Fax Group 4“ oder zweidimensionale Kodierung bezeichnet. Die Komprimierungsraten sind abhängig von den Bilddaten, im Allgemeinen liefert MMR jedoch die beste Komprimierung gefolgt von MR.
ECM Aktiv (Error Correction Mode)	Faxsysteme, die den Fehlerkorrekturmodus ECM unterstützen, prüfen während der Übertragung die Fehlerfreiheit der gesendeten Daten. Damit wird verhindert, dass Bildfehler auf Grund von Leitungsruschen auftreten.
Status: ISDN Cause Value	Nachfolgend ein Überblick über die gängigen ISDN Cause-Werte:
0x0000	GOOD
0x0001	NCPI_IGNORED
0x0002	FLAGS_IGNORED
0x0003	ALERT_IGNORED
0x1001	TOO_MANY_APPLICATIONS
0x1002	BLOCK_TOO_SMALL
0x1003	BUFFER_TOO_BIG
0x1004	MSG_BUFFER_TOO_SMALL
0x1005	TOO_MUCH_CONNECTIONS
0x1008	REG_RESOURCE_ERROR
0x1009	REG_CAPI_NOT_INSTALLED
0x1101	WRONG_APPL_ID
0x1102	BAD_MSG
0x1103	QUEUE_FULL
0x1104	GET_NO_MSG
0x1105	MSG_LOST
0x1106	WRONG_NOTIFY
0x1107	CAPI_BUSY
0x1108	RESOURCE_ERROR
0x1109	CAPI_NOT_INSTALLED
0x110A	NO_EXTERNAL_EQUIPMENT

0x110B	ONLY_EXTERNAL_EQUIPMENT
0x2001	WRONG_STATE
0x2002	WRONG_IDENTIFIER
0x2003	OUT_OF_PLCI
0x2004	OUT_OF_NCCI
0x2005	OUT_OF_LISTEN
0x2006	OUT_OF_FAX
0x2007	WRONG_MESSAGE_FORMAT
0x3001	B1_NOT_SUPPORTED
0x3002	B2_NOT_SUPPORTED
0x3003	B3_NOT_SUPPORTED
0x3004	B1_PARM_NOT_SUPPORTED
0x3005	B2_PARM_NOT_SUPPORTED
0x3006	B3_PARM_NOT_SUPPORTED
0x3007	B_STACK_NOT_SUPPORTED
0x3008	NCPI_NOT_SUPPORTED
0x3009	CIP_NOT_SUPPORTED
0x300A	CIP_UNKNOWN
0x300B	FACILITY_NOT_SUPPORTED
0x300C	DATA_LEN_NOT_SUPPORTED
0x300D	RESET_NOT_SUPPORTED
0x3301	L1_ERROR
0x3302	L2_ERROR
0x3303	L3_ERROR
0x3304	OTHER_APPL_CONNECTED
0x3311	FAX_NO_CONNECTION
0x3312	FAX_TRAINING_ERROR
0x3313	FAX_REMOTE_REJECT
0x3314	FAX_REMOTE_ABORT
0x3315	FAX_PROTOCOL_ERROR
0x3316	FAX_TX_UNDERRUN
0x3317	FAX_RX_OVERFLOW
0x3318	FAX_LOCAL_ABORT
0x3319	FAX_PARAMETER_ERROR
0x3400	OK
0x3401	Unbekannte_Rufnummer
0x3402	Keine_Route_definiert
0x3403	Keine_Route_zur_Zielrufnummer
0x3406	B-Kanal_unakzeptabel
0x3407	B-Kanal_ist_belegt
0x3410	Normal_call_clearing
0x3411	User_busy
0x3412	Keine_Reaktion_vom_Tln.
0x3413	Keine_Antwort_vom_Tln.
0x3415	Call_rejected
0x3416	Number_changed
0x341A	Non-selected_user_clearing
0x341B	Destination_out_of_order
0x341C	Invalid_number_format

0x341D	Facility_rejected
0x341E	Antwort_auf_STATUS_ENQUIRY
0x341F	Normal,_unspecified
0x3422	No_circuit/channel_available
0x3426	Network_out_of_order
0x3429	Temporary_failure
0x342A	Switching_equipment_congestion
0x342B	Access_information_discarded
0x342C	Requested_B-Channel_not_available
0x342F	Resources_unavailable,_unspecified
0x3431	Quality_of_service_unavailable
0x3432	Requested_facility_not_subscribed
0x3439	Bearer_capability_not_authorized
0x343A	Bearer_capability_not_presently_available
0x343F	Service_or_option_not_available,_unspecified
0x3441	Bearer_capability_not_implemented
0x3442	B-Channel_type_not_implemented
0x3445	Requested_facility_not_implemented
0x3446	Only_restricted_digital_information_bearer_capability_is_available
0x344F	Service_or_option_not_implemented,_unspecified
0x3451	Invalid_call_reference_value
0x3452	Identified_B-Channel_does_not_exist
0x3453	A_suspended_call_exists,_but_this_call_identity_does_not
0x3454	Call_identity_in_use
0x3455	No_call_suspended
0x3456	Call_having_the_requested_call_identity_has_been_cleared
0x3458	Incompatible_destination
0x345B	Invalid_transit_network_selection
0x345F	Invalid_message,_unspecified
0x3460	Mandatory_information_element_is_missing
0x3461	Message_type_nonexistent_or_not_implemented
0x3462	Message_not_compatible_with_call_state_or_message_type_nonexistent_or_not_implemented
0x3463	Information_element_nonexistent_or_not_implemented
0x3464	Invalid_information_element_contents
0x3465	Message_not_compatible_with_call_state
0x3466	Recovery_on_timer_expiry
0x346F	Protocol_error,_unspecified
0x347F	Interworking,_unspecified
0x3480	OK
0x3481	Unbekannte_Rufnummer
0x3482	Keine_Route_definiert
0x3483	Keine_Route_zur_Zielrufnummer
0x3486	B-Kanal_unakzeptabel
0x3487	B-Kanal_ist_belegt
0x3490	Normal_call_clearing

0x3491	User_busy
0x3492	Keine_Reaktion_vom_Tln.
0x3493	Keine_Antwort_vom_Tln.
0x3495	Call_rejected
0x3496	Number_changed
0x349A	Non-selected_user_clearing
0x349B	Destination_out_of_order
0x349C	Invalid_number_format
0x349D	Facility_rejected
0x349E	Antwort_auf_STATUS_ENQUIRY
0x349F	Normal,_unspecified
0x34A2	No_circuit/channel_available
0x34A6	Network_out_of_order
0x34A9	Temporary_failure
0x34AA	Switching_equipment_congestion
0x34AB	Access_information_discarded
0x34AC	Requested_B-Channel_not_available
0x34AF	Resources_unavailable,_unspecified
0x34B1	Quality_of_service_unavailable
0x34B2	Requested_facility_not_subscribed
0x34B9	Bearer_capability_not_authorized
0x34BA	Bearer_capability_not_presently_available
0x34BF	Service_or_option_not_available,_unspecified
0x34C1	Bearer_capability_not_implemented
0x34C2	B-Channel_type_not_implemented
0x34C5	Requested_facility_not_implemented
0x34C6	Only_restricted_digital_information_bearer_capability_is_available
0x34CF	Service_or_option_not_implemented,_unspecified
0x34D1	Invalid_call_reference_value
0x34D2	Identified_B-Channel_does_not_exist
0x34D3	A_suspended_call_exists,_but_this_call_identity_does_not
0x34D4	Call_identity_in_use
0x34D5	No_call_suspended
0x34D6	Call_having_the_requested_call_identity_has_been_cleared
0x34D8	Incompatible_destination
0x34DB	Invalid_transit_network_selection
0x34DF	Invalid_message,_unspecified
0x34E0	Mandatory_information_element_is_missing
0x34E1	Message_type_nonexistent_or_not_implemented
0x34E2	Message_not_compatible_with_call_state_or_message_type_nonexistent_or_not_implemented
0x34E3	Information_element_nonexistent_or_not_implemented
0x34E4	Invalid_information_element_contents
0x34E5	Message_not_compatible_with_call_state
0x34E6	Recovery_on_timer_expiry
0x34EF	Protocol_error,_unspecified

0x34FF	Interworking,_unspecified
--------	---------------------------